

بعض احجام كباسات باناسونيك

Category: تقنية

2024 written by www.Mbsmgroup.tn | 4

Rated voltage / Frequency	Model	ASHRAE								Voltage range
		50Hz				60Hz				
		Capacity		COP - WW		Capacity		COP - WW		
		W	kcal/hr	RSIR	RSCR	W	kcal/hr	RSIR	RSCR	
220V 50Hz/60Hz	QB51C99GAX0	128	110	1.14	-	157	135	1.17	-	170V-250V 50Hz 187V-242V 60Hz
	QB57C11GAX0	146	126	1.18	-	175	151	1.22	-	
	QB66C16GAX0	165	142	1.20	-	200	172	1.27	-	
	QB77C18GAX0	202	174	1.21	-	224	193	1.27	-	
	QB91C24GAX0	236	203	1.19	-	255	219	1.22	-	
220V 50Hz	QB66C13GAX5	165	142	1.19	-					170V-250V
	QB73C15GAX5	185	159	1.19	-					
	QB77C16GAX5	202	174	1.22	-					
	QB91C19GAX5	236	203	1.25	-					

Rated voltage / Frequency	Model	ASHRAE								Voltage range
		50Hz				60Hz				
		Capacity		COP - WW		Capacity		COP - WW		
		W	kcal/hr	CSIR	RSCR	W	kcal/hr	CSIR	RSCR	
220V 50z/60Hz	QB110C25CAX0	273	235	1.18	-	279	240	1.19	-	170V-250V 50Hz 198V-242V 60Hz

PictureS Mbsm Dot Pro : www.mbsm.pro

Picture Private Copyright WWW.MBSMGROUP.TN

بعض أحجام كباسات باناسونيك



QB 57 = 1/6

QB 66 = 1/5

QB 73 = 1/5

QB 77 = 1/5+

QB 86 = 1/4

QB 91 = 1/4

QB 110 = 1/3

Picture Private Copyright WWW.MBSMGROUP.TN

QB 57 = 1/6

QB 66 = 1/5

QB 73 = 1/5

+QB 77 = 1/5

QB 86 = 1/4

QB 91 = 1/4

QB 110 = 1/3

[qbDownload](#)

Panasonic compressor

پاناسونیک

FN43	small 1/8HP	220V	Rotary	R134a&R12
FN51	1/8HP	220V	Rotary	R134a&R12
FN57	1/6HP	220V	Rotary	R134a&R12
FN66	Big 1/6HP	220V	Rotary	R134a&R12
FN77	1/5HP	220V	Rotary	R134a&R12
FN91	1/4HP	220V	Rotary	R134a&R12
FN110	1/3HP	220v	Rotary	R134a&R12
FN43	small 1/8HP	220V	Rotary	R134a&R12
FN51	1/8HP	220V	Rotary	R134a&R12
FN57	1/6HP	220V	Rotary	R134a&R12
FN66	Big 1/6HP	220V	Rotary	R134a&R12
FN77	1/5HP	220V	Rotary	R134a&R12
FN91	1/4HP	220V	Rotary	R134a&R12
FN110	1/3HP	220v	Rotary	R134a&R12

Private Picture Copyright : WWW.MBSM.PRO

Picture Private Copyright WWW.MBSMGROUP.TN